

***dogtra* RR Deluxe**
CODE SETTING GUIDE



Dogtra Company


22912 Lockness Avenue
Torrance, CA 90501
U.S.A.

telephone (310) 534 - 0101
fax (310) 534 - 9111
toll free 1-888-811-9111




Code setting method to pair a transmitter with receivers


dogtra RR Deluxe uses code free technology so that you can match one transmitter up to eight different receivers. (16 including left and right ports) Once the code has been set, pressing a button on the specific selection dial will only activate the designated receiver. Follow the steps in order to pair a transmitter with a receiver unit.



- 1) Turn the selection dial of handheld transmitter to the desired number to pair it with the receiver.(For example, if you want to designate a receiver as your number 2 receiver, set the selection dial of the transmitter to number 2.)



- 2) Hold down the on/off button of the receiver for 5 seconds or more. Release them when the green LED blinks rapidly.



- 3) Within 5 seconds after releasing the on/off button of the receiver, hold the left and right buttons simultaneously on the handheld transmitter. When the receiver successfully

acknowledges the transmitter, the LED on the receiver should emit a constant green light for approximately 3 seconds then switch to slow steady standby blink.

- 4) Press the duck call or beep sound button on the transmitter. If the receiver emits sound, the receiver is successfully coded to the transmitter. (Repeat the process from step 1, if you have additional receivers to be coded.)